

HighNoon Dual COB Led Blinder

➤ DMX Channel

Channel	Data	Function	Remark
CH1	000 - 255	Total dimmer	0 - 100%
CH2	000 - 255	Dimmer of the first cool white LED	0 - 100%
CH3	000 - 255	Dimmer of the first warm white LED	0 - 100%
CH4	000 - 255	Dimmer of the second cool white LED	0 - 100%
CH5	000 - 255	Dimmer of the second warm white LED	0 - 100%
CH6	000 - 255	Strobe	1Hz - 20Hz
CH7	000 - 255	Speed for CH8	CH8: 51 - 200
CH8	000 - 050	Blank	CH1-CH6 WORK
	051 - 100	Auto 1	
	101 - 150	Auto 2	
	151 - 200	Auto 3	
	201 - 255	Sound	

➤ Maintenance

Clean the cooling fans when the fan is covered with duty.

Clean the lens to make the best output level of Lumen from the fixture.