

## Golden Strobe FL-1800D

### Inspection

Every Golden Strobe (FL-1800D) is thoroughly tested at the factory and shipped in perfect condition. Please notify your dealer immediately if damage occurred during shipping.

### Setting up

Golden Strobe (FL-1800D) is shipped complete, ready to use. The bracket is installed before shipping. Simply use a 20 kg rated or stronger C clamp to attach the bracket to firm trussing

### Manual Control Operation(All Dip 1-9 "OFF")

1. Plug strobe power cord into appropriate mains power supply.
2. Turn the flash speed dial (See Appendix. B) on upside of unit to adjust the flash speed.

(There is a small, white adjustment knob on the unit. This SVR can be adjusted with a screwdriver. Note, however, that this SVR is adjusted to the optimal position at the factory. Do not adjust this SVR.)

### DMX Control Operation(Any of Dip 1-9 "ON")

Use Dip switches 1-9 to set the unit to the desired DMX 512 address. Refer to the DMX chart in (Figure1).

- Connect the DMX 512 controller cable to the input socket of the strobe unit. Make sure the signal cable polarity is correct. Connect power lines. Your FL-1800D is now ready for operation with your DMX controller.

