

AVE HEX-FLAT18 RGBWAUV LED



8CH MODE

CHANNEL	FUNCTION	VALUE/RANGE	PERCENT/SETTING
1	DIMMER INTENSITY	000 ↵ 255	Intensity 0 to 100%
2	SHUTTER STROBE	000 ↵ 255	Strobe effect slow to fast
3	RED	000 ↵ 255	0-BLACK, 255-100% RED
4	GREEN	000 ↵ 255	0-BLACK, 255-100% GREEN
5	BLUE	000 ↵ 255	0-BLACK, 255-100% BLUE
6	WHITE	000 ↵ 255	0-BLACK, 255-100% WHITE
7	AMBER	000 ↵ 255	0-BLACK, 255-100% AMBER
8	UV	000 ↵ 255	0-BLACK, 255-100% UV

11CH MODE

CHANNEL	FUNCTION	VALUE/RANGE	PERCENT/SETTING
1	DIMMER INTENSITY	000 ↵ 255	Intensity 0 to 100%
2	RED	000 ↵ 255	0-BLACK, 255-100% RED
3	GREEN	000 ↵ 255	0-BLACK, 255-100% GREEN
4	BLUE	000 ↵ 255	0-BLACK, 255-100% BLUE
5	WHITE	000 ↵ 255	0-BLACK, 255-100% WHITE
6	AMBER	000 ↵ 255	0-BLACK, 255-100% AMBER
7	UV	000 ↵ 255	0-BLACK, 255-100% UV
8	COLOUR	000 ↵ 255	PRESET COLOURS
9	SHUTTER STROBE	000 ↵ 007	NO FUNCTION
		008 ↵ 99	SLOW TO FAST
		100 ↵ 149	FAST TO SLOW
		150 ↵ 199	STROBE EFFECT 1
		200 ↵ 245	STROBE EFFECT 2
		246 ↵ 255	STROBE MAX SPEED
10	STEPPING COLOUR	000 ↵ 008	NO FUNCTION
		008 ↵ 255	STEPPING COLOUR
11	CONTROL CHANNEL	000 ↵ 007	NO FUNCTION
		008 ↵ 199	STEPPING COLOUR SPEED
		200 ↵ 255	SOUND ACTIVE