

ProShop Truss Mate

Pro Shop

LED

LED Truss Mate

		<table><tr><td></td><td>2</td><td>5</td><td>5</td></tr><tr><td>g</td><td></td><td></td><td>0</td></tr><tr><td></td><td>2</td><td>5</td><td>5</td></tr><tr><td>b</td><td></td><td></td><td>0</td></tr><tr><td></td><td>2</td><td>5</td><td>5</td></tr></table>		2	5	5	g			0		2	5	5	b			0		2	5	5	<p>r: red</p> <p>g: green</p> <p>b: blue</p> <p>(LED dimmer0%~100%) with 000-255</p> <p>Default: 255</p>
	2	5	5																				
g			0																				
	2	5	5																				
b			0																				
	2	5	5																				
9	<table><tr><td>d</td><td>i</td><td>M</td><td></td></tr></table>	d	i	M		<table><tr><td></td><td>O</td><td>F</td><td>F</td></tr><tr><td>d</td><td>i</td><td>M</td><td>1</td></tr><tr><td>d</td><td>i</td><td>M</td><td>2</td></tr><tr><td>d</td><td>i</td><td>M</td><td>3</td></tr></table>		O	F	F	d	i	M	1	d	i	M	2	d	i	M	3	<p>OFF: Dimmer speed off</p> <p>DIM1: Dimmer speed fast</p> <p>DIM2: Dimmer speed middle</p> <p>DIM3: Dimmer speed slow</p> <p>Default: off</p>
d	i	M																					
	O	F	F																				
d	i	M	1																				
d	i	M	2																				
d	i	M	3																				
10	<table><tr><td></td><td>S</td><td>E</td><td>T</td></tr></table>		S	E	T	<table><tr><td></td><td>O</td><td>n</td><td></td></tr><tr><td></td><td>O</td><td>F</td><td>F</td></tr></table>		O	n			O	F	F	<p>Infrared remote mode set</p> <p>Default: On</p>								
	S	E	T																				
	O	n																					
	O	F	F																				

3.0DMX Allocation

3-CH	Function	Value	Percent/Setting
1	Red	000-255	0~100%
2	Green	000-255	0~100%
3	Blue	000-255	0~100%

8-CH	Function	Value	Percent/Setting
1	Red	000-255	0~100%
2	Green	000-255	0~100%
3	Blue	000-255	0~100%
4	Color	000-015 016-255	No Function Color Macros
5	Strobe	000-015 016-255	No Function Strobe Slow to Fast
6	Speed Programs	000-255 000-031 032-063 064-095 096-127 128-159 160-191 192-223	Programs Speed Slow to Fast No Function 0-100% 100%-0 100% -0-100% Colors Fade 3Colors Snap 7Colors Snap

ProShop Truss Mate

Pro Shop

LED

LED Truss Mate

7	Dimmer	224-255 000-255	Sound Control 0~100%
8	Dim Mode	000-051 052-101 102-152 153-203 204-255	Menu setting dimmer mode dimmer mode off dimmer mode 1 dimmer mode 2 dimmer mode 3

4.0 Technical Specifications

Rated Power	230V/11.8W	Input Voltage AC	100V-240V 50/60Hz
Current	230V/0.097A	Output AC	Yes
Fuse	T1A 250V	Dmx Channels	3/8Channels
LED Specification	RGB 3W 140°	LED quantity	3