

VSHOW WP1806 RGBWAUV IP65 LED PAR



10CH MODE

| CHANNEL | FUNCTION | VALUE/RANGE | PERCENT/SETTING |
|---------|------------------|-------------|----------------------------|
| 1 | DIMMER INTENSITY | 000 ↵ 255 | Intensity 0 to 100% |
| 2 | SHUTTER STROBE | 000 ↵ 255 | Strobe effect slow to fast |
| 3 | MACROS | 000 ↵ 019 | No Effect |
| | | 020 ↵ 029 | Red |
| | | 030 ↵ 039 | Green |
| | | 040 ↵ 049 | Blue |
| | | 050 ↵ 059 | White |
| | | 060 ↵ 069 | Red Green |
| | | 070 ↵ 079 | Red Blue |
| | | 080 ↵ 089 | Green Blue |
| | | 090 ↵ 099 | Red Green Blue White |
| | | 100 ↵ 149 | Gradient |
| | | 250 ↵ 199 | Pulse Change |
| | | 200 ↵ 229 | Jump |
| | | 230 ↵ 255 | Sound Mode |
| 4 | MACRO SPEED | 000 ↵ 255 | 0-0%, 255-100% SPEED |
| 5 | RED | 000 ↵ 255 | 0-BLACK, 255-100% RED |
| 6 | GREEN | 000 ↵ 255 | 0-BLACK, 255-100% GREEN |
| 7 | BLUE | 000 ↵ 255 | 0-BLACK, 255-100% BLUE |
| 8 | WHITE | 000 ↵ 255 | 0-BLACK, 255-100% WHITE |
| 9 | AMBER | 000 ↵ 255 | 0-BLACK, 255-100% AMBER |
| 10 | UV | 000 ↵ 255 | 0-BLACK, 255-100% UV |