

MARTIN JEM COMPACT HAZER PRO



3CH MODE

CHANNEL	FUNCTION	VALUE/RANGE	PERCENT/SETTING
1	HAZE OUTPUT LEVEL	000 ⇄ 019	IDLE RANGE (STANDBY)
		020 ⇄ 029	HAZE 5%
		030 ⇄ 039	HAZE 10%
	
		210 ⇄ 255	HAZE 100%
2	FAN OUTPUT LEVEL	000 ⇄ 019	IDLE RANGE (STANDBY)
		020 ⇄ 029	FAN 5%
		030 ⇄ 039	FAN 10%
	
		210 ⇄ 255	FAN 100%
3	SPECIAL FUNCTIONS	000 ⇄ 050	IDLE RANGE (STANDBY)
		51 ⇄ 100	PRIME (5 SECONDS TO ACTIVATE**)
		101 ⇄ 150	AUTO FAN MODE
		151 ⇄ 200	HEATER OFF / SHUTDOWN (5 SEC **)
		201 ⇄ 255	HEATER ON (NORMAL OPERATION)