

GOLDEN STROBE FL-1800D



2CH MODE

CHANNEL	FUNCTION	VALUE/RANGE	PERCENT/SETTING
1	FLASH RATE	000 ↔ 255	SLOW (2FPS) TO FAST (12FPS)
2	INTENSITY	000 ↔ 255	Dimmer